

Scarlett 2i2 Studio

User Guide



Focusrite®
www.focusrite.com

TABLE OF CONTENTS

OVERVIEW	3
Introduction	3
Features	3
Box Contents	4
System requirements	4
GETTING STARTED	5
Quick Start Tool	5
Mac users only	5
Windows only	7
All users	9
Manual Registration	9
Audio Setup in your DAW	10
Examples of Usage	12
Connecting a microphone or instrument	12
Recording with a microphone	13
Using Direct Monitoring	15
Connecting Scarlett 2i2 to headphones	15
Connecting Scarlett 2i2 to loudspeakers	16
HARDWARE FEATURES	17
Front Panel	17
Back Panel	18
SPECIFICATIONS	19
Performance Specifications	19
Physical and Electrical Characteristics	20
Scarlett CM25 MkIII Microphone Specifications	21
Scarlett HP60 MkIII Headphones Specifications	21
TROUBLESHOOTING	22
COPYRIGHT AND LEGAL NOTICES	22

OVERVIEW

Introduction

Thank you for purchasing the Third Generation Scarlett 2i2 Studio, part of the range of Focusrite professional audio interfaces incorporating high quality Focusrite analogue pre-amplifiers. You now have a simple, compact and complete solution for recording with a microphone or directly from instruments, by routing high quality audio to and from your computer.

In developing the Third Generation series of Scarlett interfaces, we have made further improvements to both performance and features. Audio specifications have been upgraded throughout the unit to give you greater dynamic range and even lower noise and distortion; additionally, the mic preamp now accepts higher input levels. An important enhancement is the inclusion of Focusrite's AIR function. Individually selectable on each channel, AIR subtly modifies the preamp's frequency response to model the sonic characteristics of our classic transformer-based ISA microphone preamps. When recording with good quality microphones, you will notice an enhanced clarity and definition in the important mid to high frequency range, just where it is most needed for vocals and many acoustic instruments. We have also enhanced the Direct Monitor feature found on previous Scarletts: now you can monitor as you record in either mono or stereo, with zero latency. Third Generation Scarlett interfaces are now class compliant on macOS: this means they are plug-and-play, so no need to install a driver if you are a Mac user.

This User Guide provides a detailed explanation of the components to help you achieve a thorough understanding of the product's operational features. We recommend that both users that are new to computer-based recording, as well as more experienced users, take the time to read through the User Guide so that you are fully aware of all the possibilities that the Scarlett Studio components and accompanying software has to offer. If the main User Guide sections do not provide the information you need, be sure to consult <https://support.focusrite.com/>, which contains a comprehensive collection of answers to common technical support queries.

Features

The Scarlett 2i2 Studio comprises a Scarlett 2i2 audio interface, a Scarlett Studio CM25 MkIII studio quality condenser microphone, a pair of Scarlett Studio HP60 MkIII reference quality headphones and all the necessary software to get you started as quickly as possible.

The Scarlett 2i2 hardware interface is the key component in the Scarlett 2i2 Studio; this provides the means of connecting the CM25 MkIII (or other) microphone, musical instruments or line level audio signals to a computer running macOS or Windows. The signals applied at the 2i2's physical inputs can be routed to your recording software at up to 24-bit, 192 kHz resolution via a USB connection. Similarly, the recording software's monitor or recorded output will appear at the 2i2's physical outputs. (Note - audio recording software is frequently referred to as a "Digital Audio Workstation", or "DAW", and the term "DAW" is used throughout this user guide.)

The physical outputs can be connected to an amplifier and speakers, powered monitors, headphones, analogue mixer or any other analogue audio equipment that you wish to use.

Box Contents

You should find that your Scarlett 2i2 Studio comprises:

- Scarlett 2i2 (3rd Gen.) audio interface
- Scarlett Studio CM25 MkIII condenser microphone and microphone clip
- Scarlett Studio HP60 MkIII headphones
- Red XLR microphone cable (3 m)
- USB cable, Type 'A' to Type 'C'
- Getting Started Guide (printed on inside of box lid)
- Important Safety Information

System requirements

The easiest way to check that your computer's operating system (OS) is compatible with the Scarlett 2i2 is to use our online OS Checker at <https://customer.focusrite.com/downloads/os>. As new OS versions become available over time, you can continue to check for further compatibility information by searching our Help Centre at <https://support.focusrite.com/hc/en-gb>.

GETTING STARTED

With the Third Generation, Scarlett interfaces introduce a new, faster way of getting up and running, using the Scarlett Quick Start tool. All you need to do is connect your Scarlett 2i2 to your computer. Once connected, you will see that the device is recognised by your PC or Mac and the Quick Start tool will guide you through the process from there.

IMPORTANT: The Scarlett 2i2 has a single USB 2.0 Type C port (on the rear panel): connect it to your computer using the USB cable provided. Note that Scarlett 2i2 is a USB 2.0 device, and thus the USB connection requires a USB 2.0+ compliant port on your computer.

The Scarlett 2i2 gets its power from your computer via the USB connection: there is no need for a separate power supply. However, we do recommend that when using it with a laptop, the laptop should be powered using its AC adaptor, as otherwise the battery will run down faster than when powering the laptop alone.

Your computer will initially treat your Scarlett as a Mass Storage Device (MSD), and during its first connection, the Scarlett will be in “MSD Mode”.

Quick Start Tool


We have tried to make registering your Scarlett 2i2 as simple as possible. The procedure will probably be self explanatory, but we have described each step below, so you can see how they should appear on either a PC or a Mac.

Mac users only:


On connecting your Scarlett 2i2 to your Mac, a Scarlett icon will appear on the desktop:



Double-click on the icon to open the Finder window shown below:



Double-click on the "Click Here to Get Started.url" icon. This will redirect you to the Focusrite website, where we recommend that you register your device:




Click on "Let's get you started", and you'll be presented with a form which will be partly prefilled for you automatically. On submitting the form, options will be presented to either go straight to the downloads area to get the software for your Scarlett, or to follow a step by step setup guide based on your choices. Once you have installed the Focusrite Control software to setup and configure your interface, the Scarlett will be switched out of MSD mode so that it no longer appears as a Mass Storage Device when connected to your computer.

Your OS should automatically switch the computer's default audio inputs and outputs to the Scarlett 2i2. To verify this, go to **System Preferences > Sound**, and ensure that the input and output are set to **Scarlett 2i2**. For more detailed setup options on a Mac, open **Applications > Utilities > Audio MIDI Setup**.


Windows only:

On connecting your Scarlett 2i2 to your PC, a Scarlett icon will appear on the desktop:




(Note that the drive letter may be something other than F:, depending what other devices you have connected to your PC).


Double-click on the pop-up message to open the dialogue box shown below:



Double-click on “Open folder to view files”: this will open an Explorer window:



Double-click “Click Here to Get Started”. This will redirect you to the Focusrite website, where we recommend that you register your device:



Click on “Let’s get you started”, and you’ll be presented with a form which will be partly prefilled for you automatically. On submitting the form, options will be presented to either go straight to the downloads area to get the software for your Scarlett, or to follow a step-by-step setup guide based on your choices. Once you have installed the Focusrite Control software to setup and configure your interface, the Scarlett will be switched out of MSD mode so that it no longer appears as a Mass Storage Device when connected to your computer.

Your OS should automatically switch the computer’s default audio inputs and outputs to be the Scarlett 2i2. To verify this, right click on the Sound icon on the taskbar and select **Sound Settings**, and set the Scarlett as the Input and Output Device.

All users:

Note that a second file - "More Info & FAQs" - is also available during the initial set-up process. This file contains some additional information about the Focusrite Quick Start tool which you may find helpful if you have any issues with the procedure.

Once registered, you will have immediate access to the following resources:

- Focusrite Control (Mac and Windows versions available) - see NOTE below
- Multi-language User Guides

Licence codes and links will be provided for the following bundled software within your account page.

- Pro Tools | First
- Ableton Live Lite
- Focusrite Red 2 & 3 Plug-in Suite
- Softube Time and Tone bundle
- XLN Addictive Keys
- LoopMasters sample library
- Plug-in Collective Offers

NOTE: Installing Focusrite Control will also automatically install the correct driver for your device. Focusrite Control is available to download at any time, even without registering: see "Manual Registration" below.

Manual Registration

If you decide to register your Scarlett 2i2 at a later date you can do so at <https://customer.focusrite.com/user/register>. You will need to enter the Serial Number manually: this number can be found on the base of the interface itself, and also on the barcode label on the side of the box.

We recommend that you download and install our Focusrite Control application, as this will disable MSD mode and unlock the full potential of the interface. Initially, when in MSD mode, the interface will function at sample rates up to 48 kHz. Once Focusrite Control is installed on your computer, you can work at sample rates up to 192 kHz. If you decide not to download and install Focusrite Control immediately, it can be downloaded at any time from <https://customer.focusrite.com/support/downloads>.


In order to force your Scarlett 2i2 out of MSD mode without first registering it, connect it to your host computer and press and hold the **48V** button for five seconds. This will ensure that your Scarlett 2i2 has full functionality. Please bear in mind that should you wish to register your Scarlett 2i2 after taking this action, you will need to do so manually, as explained above.

Audio Setup in your DAW

The Scarlett 2i2 is compatible with any Windows-based DAW that supports ASIO or WDM and any Mac-based DAW that uses Core Audio. After following the Getting Started procedure described above, you can start using the Scarlett 2i2 with the DAW of your choice. To allow you to get started if you do not already have a DAW application installed on your computer, both Pro Tools | First and Ableton Live Lite are included; these will be available to you once you've registered your Scarlett 2i2. If you need help installing either DAW, please visit our Getting Started pages at <https://focusrite.com/get-started>, where Getting Started videos are available.


Operating instructions for Pro Tools | First and Ableton Live Lite are beyond the scope of this User Guide, but both applications include a full set of Help files. Instructions are also available at www.avid.com and www.ableton.com respectively.

Please note - your DAW may not automatically select the Scarlett 2i2 as its default I/O device. In this case, you must manually select **Focusrite USB ASIO** as the driver on your DAW's Audio Setup* page. Please refer to your DAW's documentation (or Help files) if you are unsure where to select the ASIO or Core Audio driver. The example below shows the correct configuration in the Ableton Live Lite **Preferences** panel (Windows version shown).



* Typical names. Terminology may differ slightly between DAWs.

Once the Scarlett 2i2 is set as the preferred Audio Device* in your DAW, Inputs 1 & 2 and Outputs 1 & 2 will appear in your DAW's Audio I/O preferences. Depending on your DAW, you may need to enable certain inputs or outputs before use. The two examples below show Inputs 1 & 2 and Outputs 1 & 2 enabled in the Ableton Live Audio Preferences.




* Typical names. Terminology may differ slightly between DAWs.

Examples of Usage

The Scarlett 2i2 is an excellent choice for several different recording and monitoring applications. Some typical configurations are shown below.

Connecting a microphone or instrument



This setup illustrates the most typical configuration for recording with DAW software on your Mac or PC. In this case, you might record guitar through Input 1 and vocals through Input 2 into your DAW, while monitoring the playback from the DAW via headphones (or speakers).

The front panel input sockets are “Combo” type, which accept either an XLR male connector (you will probably have one on the end of your microphone cable) or a 1/4” (6.35 mm) jack plug. If you are using a capacitor (or “condenser”) microphone, you will need to turn on the 48 V phantom power. Phantom power should not be used when other types of microphone – e.g., dynamic or ribbon – are in use.

Note the Scarlett 2i2 has no “Mic/line” switch – the Focusrite preamplifier stage is automatically configured for a microphone when you plug an XLR into the input, and for a line or instrument when you connect a jack plug. Press the **INST** button (illuminates red) if you are connecting a musical instrument (a guitar in the example) via an ordinary 2-pole (TS) guitar jack. When INST mode is not selected, you can connect a line level source such as a keyboard, synthesiser or the balanced output of an external audio mixer via a 3-pole (TRS) jack. Note the Combo connector accepts both TRS and TS types of jack plug.

Recording with a microphone

The Scarlett Studio CM25 MkIII microphone supplied with Scarlett Studio is a studio quality condenser mic which is ideal for recording vocals and most acoustic instruments. Connect the CM25 MkIII to one of the Scarlett 2i2’s two front panel inputs with the cable supplied.

Condenser microphones (also sometimes referred to as “capacitor” microphones) require a source of DC power to operate. This is almost always supplied by “phantom” powering from the mic pre-amp to which the mic is connected (early and special-purpose condenser mics might have a separate power supply). For the CM25 MkIII (or any other condenser mic) to work with the Scarlett 2i2, press the 48V button on the front panel (see front panel diagram on page 17 item [3]). We recommend that you follow the following sequence:

- Turn the input gain [2] to minimum
- Connect the microphone
- Press the 48V button
- Increase the input gain to the required level




Other types of microphone (including the common dynamic type) do not require phantom power, and may suffer damage if phantom power is applied. Some cheaper condenser microphones are able to operate from a lower phantom power voltage – typically 15 V. You should check the mic spec to see if it is safe to operate it from 48 V; if not, obtain a suitable external phantom power supply.

Microphone Dos and Don'ts

A guide to microphone technique is beyond the scope of this User Guide (though many excellent books and online video tutorials on the subject are available), but if you are new to recording with a studio quality microphone, you need to observe a few golden rules.

DO use a mic stand. The CM25 MkIII has an industry-standard 5/8" threaded insert which allows it to be mounted on most mic stands. An 3/8" adaptor is included to allow it to be fitted to mic stands that have this thread size. Inexpensive short, long and boom stands are readily available from music stores.

DO observe the microphone's orientation. The CM25 MkIII has a cardioid response pattern; this basically means that it has a "front" and a "back", and if you point it the wrong way round, it will sound odd. The front of the CM25 MkIII can be identified by the CM25 MkIII logo.



DON'T ignore the room acoustics. You probably won't have the luxury of a recording studio's perfect acoustics. Be aware of how reverberant the room is. Reverberation is neither good nor bad, but frequently inappropriate! Some instruments will benefit from being recorded in a reverberant space, others won't. A "dead" acoustic is generally better than a "live" one, because reverberation can be added electronically in the recording process, but room reverberation on the recording can't be removed.

DON'T blow into a microphone to test it! Lightly rub or scratch the grille instead.

DO experiment with microphone placement. Remember you will not only be recording the vocal or instrument, but the effect of the microphone position relative to the voice or instrument as well, and this will be affected by the room acoustics. Moving the mic around, and trying recordings at different distances and angles to the source will produce different sounding results, some of which will be better than others.

DO use the CM25 MkIII to mic up a guitar amplifier if you want to include the contribution to the sound that the amplifier makes. But be aware that very high sound levels can be produced very close to the loudspeaker, and if you need high volume, you may get a better result by moving the mic away from the amplifier. Also, be aware that you will get a subtly different sound if you point the mic at the centre of the loudspeaker cone compared to the edge.

DON'T forget that a microphone is utterly unforgiving – it will not only pick up what you are trying to record, but any other sound source in the room, like a clock, the aircon, heating, or a chair creaking. You know how you take those holiday photos of a great bit of scenery and it's only when you look at the pictures later that you see the power cables right across the view? It's the same with recording. You might not notice extraneous sounds at the time, but the mic will and you'll hear them on the recording. To remove any unwanted low frequency rumble, it is advisable that the High Pass Filter (HPF) on the mic's DAW channel is enabled.

Using Direct Monitoring

You will frequently hear the term “latency” used in connection with digital audio systems. In the case of the simple DAW recording application described above, latency will be the time it takes for your input signals to pass through your computer and audio software. Latency can be a problem for a performer who wishes to record while monitoring their input signals.

The Scarlett 2i2 is fitted with a “Direct Monitoring” option, which overcomes this problem. Setting the front panel **DIRECT MONITOR** control to either MONO  or STEREO  will route your input signals directly to the Scarlett 2i2’s headphone and main monitor outputs. This enables you to hear yourself with zero latency – i.e., in “real time” – along with the computer playback. The input signals to your computer are not affected in any way by this setting.

In MONO mode, Inputs 1 and 2 are routed equally to the two outputs (both the rear panel outputs and headphones) so that they both appear in the centre of the stereo image. This is useful when you are recording two separate instruments or an instrument and a vocal, where there is no need for the two signals to be specifically located in the stereo image. Further examples would be an acoustic and an electric guitar, a bass which is both mic’d and DI’d or two separate mics differently positioned on a guitar amplifier.

In STEREO mode, Input 1 is routed to the left output channel and Input 2 to the right. Use this mode if you are recording something that is inherently stereo in nature. Monitoring in stereo will give you a more accurate impression of the sound stage. Examples are any situation where two microphones are being used to deliberately capture a stereo image such as a pair of overhead drum mics, a single stereo mic recording an orchestra or other ensemble, or the stereo outputs of an electronic source such as a piano, synthesiser or FX unit.

When using Direct Monitoring, ensure that your DAW software is not set to route its input (what you are currently recording) to its output. If it is, you will hear yourself “twice”, with one signal audibly delayed as an echo.

Monitoring with **DIRECT MONITOR** set to OFF can be useful when using an FX plug-in to your DAW to create a stereo effect which contributes to the live performance. In this way, you will be able to hear exactly what is being recorded, complete with the FX. However, some latency may result, the amount depending on the DAW’s buffer size and processing power of the computer.

Connecting Scarlett 2i2 to headphones

The Scarlett 2i2 Studio package includes a pair of high quality HP60 MkIII headphones. They are lightweight and durable, and should prove comfortable to wear for extended periods. The headband is adjustable.

The HP60 MkIII headphones have a low noise, oxygen-free copper cable, fitted with a ¼” (6.35 mm) 3-pole (TRS) jack plug. This should be connected to the socket at the right hand side of the Scarlett 2i2 front panel (indicated by a  symbol). The Scarlett 2i2’s headphone output is, of course, suitable for use with other models of headphones: if they terminate in a 3.5 mm TRS “mini jack”, use a TRS ¼”-to-3.5 mm jack adaptor

The volume in the headphones can be adjusted by the rotary control immediately above the socket.




Please be aware that headphones are capable of generating very high sound pressure levels at the ear; prolonged exposure to high sound levels may impair your hearing. Never turn headphones volume up any further than necessary.


Connecting Scarlett 2i2 to loudspeakers

The ¼" jack outputs on the rear panel can be used to connect monitoring speakers. Self-powered monitors incorporate internal amplifiers with a volume control, and may be connected directly. Passive loudspeakers will require a separate stereo amplifier; in this case, the outputs should be connected to the amplifier's inputs.

Connecting active speakers



Connecting passive speakers




The line outputs are 3-pole (TRS) ¼" (6.35 mm) jack sockets, and are electronically balanced. Typical consumer (Hi-Fi) amplifiers and small powered monitors will have unbalanced inputs, either on phono (RCA) sockets, or via a 3.5 mm 3-pole jack plug intended for direct connection to a computer. In either case, use a suitable connecting cable with jack plugs at one end.

Professional power amplifiers will generally have balanced inputs; we highly recommend using balanced cables to connect these to the outputs of the Scarlett 2i2.

NOTE: You run the risk of creating an audio feedback loop if loudspeakers are active when you are monitoring a microphone! We recommend that you always turn off (or turn down) monitoring loudspeakers while recording, and use headphones when overdubbing.

HARDWARE FEATURES

Front Panel




The Front Panel includes the input connectors for Mic, Line and Instrument signals, as well as the input gain and monitoring controls.

1. Inputs 1 & 2 – “Combo” type input sockets - connect microphones, instruments (e.g., guitar), or line level signals here. Combo sockets accept both XLR and ¼” (6.35 mm) jacks. Microphones will normally be connected using XLR plugs: instruments and line level signals should be connected via ¼” (6.35 mm) jack plugs of either TR or TRS type. The preamp gain is appropriate for microphones when an XLR plug is inserted, and for higher level signals when a jack plug is inserted. Do not connect anything other than a microphone - e.g., the output of a sound module or FX unit - via an XLR plug, as the signal level will overload the preamp, resulting in distortion; also, if phantom power is enabled, the equipment may be damaged.
2. **GAIN 1** and **GAIN 2** – adjust the preamp gain for signals on inputs 1 and 2 respectively. The gain controls have concentric tri-colour LED ‘rings’ to confirm signal level: green indicates an input level of at least -24 dBFS (i.e., ‘signal present’), the ring then turns amber at -6 dBFS to indicate that the signal is close to clipping, and finally to red at 0 dBFS (digital clipping).
3. **48V** – phantom power switch for mic inputs - enables 48 V phantom power at the XLR contacts of both Combo connectors.
4. **INST** – Line/Instrument level switches for each input which alter gain and input impedance to suit either instrument or line level signals. ‘INST’ illuminates red when Instrument mode is selected. Note that INST may also be selected from Focusrite Control.
5. **AIR** – two switches enabling AIR mode for each input. AIR modifies the frequency response of the input stage to model the classic, transformer-based Focusrite ISA microphone preamps. ‘AIR’ illuminates yellow when the mode is selected. Note that AIR may also be selected from Focusrite Control.
6. **MONITOR** – main monitor output level control - sets the output level at the main (rear panel) outputs **LEFT** and **RIGHT**.

7.  USB LED – illuminates when the unit receives USB bus power and is confirmed by the computer as connected and operating correctly.
8. **DIRECT MONITOR** – this switch determines how input sources are to be monitored and steps between three Direct Monitoring modes: OFF, MONO and STEREO. When set to OFF, monitoring of input sources is via the DAW; in MONO or STEREO, monitoring is taken directly from the preamp inputs and is therefore free of any possible latency effect. The symbols  or  illuminate green to indicate selection of mono and stereo modes respectively.
9.  Headphone level – adjusts the output level at the front panel stereo headphone output.
10.  Headphone socket – 1/4" TRS output jack. If your headphones have a 1/4" TRS jack plug, connect them directly; if they have a 3.5 mm TRS "mini jack", use a TRS 1/4"-to-3.5 mm jack adaptor. Note that it is likely that headphones fitted with 4-pole TRRS plugs will not operate correctly.

Back Panel



11. **K** (Kensington security lock) – secure your Scarlett 2i2 to a suitable structure if desired.
12.  **USB 2.0 port** – Type C connector; connect to your computer with cable supplied.
13. **LINE OUTPUTS: LEFT and RIGHT** – 2 x 1/4" (6.35 mm) TRS jack sockets; +10 dBu output level (variable), electronically balanced. Either 1/4" TRS (balanced connection) or TS (unbalanced connection) jack plugs can be used.

SPECIFICATIONS

Performance Specifications

NOTE: All performance figures measured in accordance with the provisions of AES17, as applicable.

Clock Source	Internal
Supported sample rates	44.1 kHz, 48 kHz, 88.2 kHz, 96 kHz, 176.4 kHz, 192 kHz
Microphone Inputs	
Dynamic Range	111 dB (A-weighted)
Frequency Response	20 Hz to 20 kHz ± 0.1 dB
THD+N	<0.0012% (minimum gain, -1 dBFS input with 22 Hz/22 kHz bandpass filter)
Noise EIN	-128 dB (A-weighted)
Maximum Input Level	+9 dBu at minimum gain
Gain Range	56 dB
Input impedance	3 kohms
Line Inputs	
Dynamic Range	110.5 dB (A-weighted)
Frequency Response	20 Hz to 20 kHz ± 0.1 dB
THD+N	<0.002% (minimum gain, -1 dBFS input with 22 Hz/22 kHz bandpass filter)
Maximum Input Level	+22 dBu at minimum gain
Gain Range	56 dB
Input impedance	60 kohms
Instrument Inputs	
Dynamic Range	110 dB (A-weighted)
Frequency Response	20 Hz to 20 kHz ± 0.1 dB
THD+N	<0.03% (minimum gain, -1 dBFS input with 22 Hz/22 kHz bandpass filter)
Maximum Input Level	+12.5 dBu at minimum gain
Gain Range	56 dB
Input impedance	1.5 Mohms
Line Outputs 1 & 2 (balanced)	
Dynamic Range	108.5 dB (A-weighted)
Maximum Output Level	+15.5 dBu at minimum gain; balanced outputs
THD+N Outputs (1-2)	<0.002% (maximum level, -1 dBFS input 1 kHz with 20 Hz/22 kHz bandpass filter)
Output impedance	430 ohms
Headphone Outputs	
Dynamic Range	104 dB (A-weighted)
Maximum Output Level	7 dBu

THD+N	<0.002% (maximum level, -1 dBFS input, 1 kHz, with 20 Hz/22 kHz bandpass filter)
Output impedance	<1 ohm

Physical and Electrical Characteristics

Analogue Inputs	
Connectors	XLR "Combo" type: Mic/Line/Inst (Inputs 1-2) on front panel
Mic/Line switching	Automatic
Line/Instrument switching	2 x front panel switches or via Focusrite Control
Phantom power	Shared 48 V phantom power switch for inputs 1 & 2 (XLR connections only)
AIR function	Front panel switch or via Focusrite Control
Analogue Outputs	
Balanced outputs	2 x ¼" TRS jacks on rear panel
Stereo headphone output	¼" TRS jack on front panel
Main output level control	On front panel
Headphones level control	
Other I/O	
USB	1 x USB 2.0 Type C connector
Front Panel Indicators	
USB power	Green LED
Gain Halos	Tri-colour LED rings (concentric with GAIN controls)
Phantom power	Red LED
Instrument mode	2 x red LEDs
AIR mode	2 x amber LEDs
Direct Monitor mode	2 x green LEDs
Weight and Dimensions	
W x H x D	175 mm x 47.5 mm x 99 mm 6.89 in x 1.87 in x 3.89 in
Weight	470 g 1.04 lb

Scarlett CM25 MkIII Microphone Specifications

Capsule	
Element	Electret Condenser
Diameter	20 mm
Polar Pattern	Unidirectional (cardioid)
Performance and Electrical characteristics	
Sensitivity	-36 dB \pm 2 dB (0 dB = 1 V/Pa at 1 kHz)
Frequency Response	20 Hz to 20 kHz
Impedance	200 ohms \pm 30% (at 1 kHz)
Recommended Load Impedance	>10 kohms
Equivalent Noise Level	16 dBA (A-weighted IEC651)
S/N Ratio	74 dB
Power Requirement	48 V phantom supply
Current	3 mA
Performance and Electrical characteristics	
Mounting	Standard 5/8" female; 3/8" adaptor supplied
Net Weight	496 g, inc. DCZ-16 mic clip
Body Dimensions	49.5 mm (dia.) x 158 mm (length) 1.95 in (dia.) x 6.22 in (length)

Scarlett HP60 MkIII Headphones Specifications

Type	Closed-back
Drive diameter	50 mm
Impedance	32 ohms
Sensitivity	98 dB \pm 3 dB
Frequency response	20 Hz to 20 kHz
Max. power rating	1.2 W
Cable length	3 m (approx.)
Connectors	3.5 mm stereo jack, 6.35 mm screw-on adaptor
Weight	288 g (inc. cable)

TROUBLESHOOTING

For all troubleshooting queries, please visit the Focusrite Answerbase at support.focusrite.com/ where you will find articles covering numerous troubleshooting examples.

COPYRIGHT AND LEGAL NOTICES

Your Scarlett 2i2 has a two-year warranty, valid anywhere in the world, against manufacturing defects. Full Terms and Conditions of the Warranty can be found at <https://focusrite.com/warranty>.

Focusrite is a registered trade mark and Scarlett 2i2 and Scarlett 2i2 Studio are trade marks of Focusrite Audio Engineering Limited.

All other trade marks and trade names are the property of their respective owners.
2019 © Focusrite Audio Engineering Limited. All rights reserved.